

# /domain/<DOMAIN>/ss/feature-codes

feature- .

- [clean](#)
- [info](#)
- [set](#)

## clean

, .  
:  
/domain/<DOMAIN>/ss/feature-codes/clean

clean <Family> <FeatureKey>

<Family> - ;  
<FeatureKey> - feature- .

- deactivate - ;
- activate - .

:  
Flash.

```
admin@[mycelium1@ecss1#ECSS-T 000009]:/$ domain/biysk.local/ss/feature-codes/clean vip_call use
Feature code successfully restored

[exec at: 29.05.2019 10:26:41, exec time: 454ms, nodes: dsl@ecss1]
```

## info

, .  
:  
/domain/<DOMAIN>/ss/feature-codes/info

info [<Family>]

<FAMILY> - , .

admin@[mycelium1@ecss1#ECSS-T 000009]:/\$ domain/biysk.local/ss/feature-codes/info					
W	SS name	Feature key Description	Feature code		Sample
	3way	activate	*95	*95#	Activate '3-
	Way Conference'				
	3way	activate_pulse	1195	1195#	Activate '3-
	Way Conference' (pulse)				
	3way	deactivate	#95	#95#	Deactivate
	'3-Way Conference'				
	3way	deactivate_pulse	1295	1295#	Deactivate
	'3-Way Conference' (pulse)				
	3way	test	*#95	*#95#	Check '3-Way

Conference'					
3way	test_pulse	1395	1395#		Check '3-Way
Conference' (pulse)					
3way	trigger	*D95	*D95#		Activate
/Deactivate '3-Way Conference' in trigger mode					
ALL	deactivate	#50	#50*PIN#		Deactivate
all supplementary services					
ALL	deactivate_pulse	1450	1450#		Deactivate
all supplementary services (pulse)					
PIN	activate	*29	*29*OLD_PIN*NEW_PIN*NEW_PIN#		Change PIN
code					
acb	activate	*16	*16#		Activate
'Anonymous Call Blocking'					
acb	activate_pulse	1116	1116#		Activate
'Anonymous Call Blocking' (pulse)					
acb	deactivate	#16	#16#		Deactivate
'Anonymous Call Blocking'					
acb	deactivate_pulse	1216	1216#		Deactivate
'Anonymous Call Blocking' (pulse)					
acb	test	*#16	*#16#		Check
'Anonymous Call Blocking'					
acb	test_pulse	1316	1316#		Check
'Anonymous Call Blocking' (pulse)					
acb	trigger	*D16	*D16#		Activate
/Deactivate 'Anonymous Call Blocking' in trigger mode					
alarm	activate_daily	*56	*56*ARM_NUMBER*DAY*HHMM#		Activate
daily alarm					
alarm	activate_one_time	*55	*55*ARM_NUMBER*DAY*HHMM#		Activate one-
time alarm					
alarm	deactivate	#55	#55*ARM_NUMBER#		Deactive
alarm (one or all)					
alarm	test	*#55	*#55*ARM_NUMBER#		Check alarm
status					
alarm	trigger	*D55	*D55*ARM_NUMBER*DAY*HHMM#		Activate
/Deactivate one-time alarm in trigger mode					
alarm	trigger	*D56	*D56*ARM_NUMBER*DAY*HHMM#		Activate
/Deactivate daily alarm in trigger mode					
auto_redial	use_all	*38	*38*NUMBER#		Use 'Auto
redial' in any mode					
auto_redial	use_busy	*37	*37*NUMBER#		Use 'Auto
redial' in busy mode					
auto_redial_with_callback	use	*39	*39#		Use 'Auto
redial with callback'					
callback	use	*40	*40#		Use
'CallBack'					
cc_agent	call_agent	*165	*165*AGENT_ID#		Call Contact-
Center Agent					
cc_agent	complete	#161	#161#		Complete
conversation Contact-Center Agent					
cc_agent	enter_auxwork	#162	#162#		Enter
AuxWork Contact-Center Agent					
cc_agent	login	*160	*160*AGENT_ID*PASSWORD#		Login
Contact-Center Agent					
cc_agent	logout	#160	#160#		Logout
Contact-Center Agent					
cc_agent	make_available	#163	#163#		Make
Available Agent					
cc_agent	set_default_supervise_mode	*167	*167*MODE#		Set default
supervise mode of Contact-Center supervisor					
cc_agent	supervise	*164	*164*AGENT_ID*MODE#		Supervise
Contact-Center Agent					
cc_agent	supervise2	*166	*166*AGENT_ID*MODE#		Supervise
Contact-Center Agent					
cfb	activate	*22	*22*NUMBER#		Activate
'Call Forwarding Busy'					
cfb	activate_pulse	1122	1122#		Activate
'Call Forwarding Busy' (pulse)					
cfb	deactivate	#22	#22#		Deactivate
'Call Forwarding Busy'					
cfb	deactivate_pulse	1222	1222#		Deactivate
'Call Forwarding Busy' (pulse)					

cfb	test	*#22	*#22#	Check 'Call
Forwarding Busy'				
cfb	test_number_pulse	1422	1422#	Check 'Call
Forwarding Busy' on specific number (pulse)				
cfb	test_pulse	1322	1322#	Check 'Call
Forwarding Busy' (pulse)				
cfb	trigger	*D22	*D22*NUMBER#	Activate
/Deactivate 'Call Forwarding Busy' in trigger mode				
cfnr	activate	*27	*27*NUMBER#	Activate
'Call Forwarding No Reply'				
cfnr	activate_pulse	1127	1127#	Activate
'Call Forwarding No Reply' (pulse)				
cfnr	deactivate	#27	#27#	Deactivate
'Call Forwarding No Reply'				
cfnr	deactivate_pulse	1227	1227#	Deactivate
'Call Forwarding No Reply' (pulse)				
cfnr	test	*#27	*#27*NUMBER#	Check 'Call
Forwarding No Reply'				
cfnr	test_number_pulse	1427	1427#	Check 'Call
Forwarding No Reply' on specific number (pulse)				
cfnr	test_pulse	1327	1327#	Check 'Call
Forwarding No Reply' (pulse)				
cfnr	trigger	*D27	*D27*NUMBER#	Activate
'Call Forwarding No Reply' in trigger mode				
cfnr_type2	activate	*42	*42*NUMBER#	Activate
'Call Forwarding No Reply without notification'				
cfnr_type2	deactivate	#42	#42*NUMBER#	Deactivate
'Call Forwarding No Reply without notification'				
cfnr_type2	test	*#42	*#42#	Check 'Call
Forwarding No Reply without notification'				
cfnr_type2	trigger	*D42	*D42*NUMBER#	Activate
/Deactivate 'Call Forwarding No Reply without notification' in trigger m				
ode				
cfos	activate	*24	*24*NUMBER#	Activate
'Call Forwarding Out of Service'				
cfos	activate_pulse	1124	1124#	Activate
'Call Forwarding Out of Service' (pulse)				
cfos	deactivate	#24	#24#	Deactivate
'Call Forwarding Out of Service'				
cfos	deactivate_pulse	1224	1224#	Deactivate
'Call Forwarding Out of Service' (pulse)				
cfos	test	*#24	*#24#	Check 'Call
Forwarding Out of Service'				
cfos	test_number_pulse	1424	1424#	Check 'Call
Forwarding Out of Service' on specific number (pulse)				
cfos	test_pulse	1324	1324#	Check 'Call
Forwarding Out of Service' (pulse)				
cfos	trigger	*D24	*D24*NUMBER#	Activate
/Deactivate 'Call Forwarding Out of Service' in trigger mode				
cft	activate	*28	*28*DAYS*HH1MM1HH2MM2*...*NUMBER#	Activate
'Call Forwarding Unconditional Time Dependent'				
cft	deactivate	#28	#28#	Deactivate
'Call Forwarding Unconditional Time Dependent'				
cft	test	*#28	*#28#	Check 'Call
Forwarding Unconditional Time Dependent'				
cft	trigger	*D28	*D28*DAYS*HH1MM1HH2MM2*...*NUMBER#	Activate
/Deactivate 'Call Forwarding Unconditional Time Dependent' in trigger mo				
de				
cfu	activate	*21	*21*NUMBER#	Activate
'Call Forwarding Unconditional'				
cfu	activate_pulse	1121	1121#	Activate
'Call Forwarding Unconditional' (pulse)				
cfu	deactivate	#21	#21#	Deactivate
'Call Forwarding Unconditional'				
cfu	deactivate_pulse	1221	1221#	Deactivate
'Call Forwarding Unconditional' (pulse)				
cfu	test	*#21	*#21#	Check 'Call
Forwarding Unconditional'				
cfu	test_number_pulse	1421	1421#	Check 'Call

Forwarding Unconditional' on specific number (pulse)				
cfu	test_pulse	1321	1321#	Check 'Call
Forwarding Unconditional' in common (pulse)				
cfu	trigger	*D21	*D21*NUMBER#	Activate
/Deactivate 'Call Forwarding Unconditional' in trigger mode				
cfu_type2	activate	*41	*41*NUMBER#	Activate
'Call Forwarding Unconditional without notification'				
cfu_type2	deactivate	#41	#41*NUMBER#	Deactivate
'Call Forwarding Unconditional without notification'				
cfu_type2	test	*#41	*#41#	Check 'Call
Forwarding Unconditional without notification'				
cfu_type2	trigger	*D41	*D41*NUMBER#	
ActivateDeactivate 'Call Forwarding Unconditional without notification' in trigg				er
mode				
chold	activate	*94	*94#	Activate
'Call hold'				
chold	activate_pulse	1194	1194#	Activate
'Call hold' (pulse)				
chold	deactivate	#94	#94#	Deactivate
'Call hold'				
chold	deactivate_pulse	1294	1294#	Deactivate
'Call hold' (pulse)				
chold	test	*#94	*#94#	Check 'Call
hold'				
chold	test_pulse	1394	1394#	Check 'Call
hold' (pulse)				
chold	trigger	*D94	*D94#	Activate
/Deactivate 'Call hold' in trigger mode				
clip	test	*#30	*#30#	Check
'Calling Line Identification Presentation'				
clir	activate	*31	*31#	Activate
'Calling Line Identification Restriction'				
clir	activate_pulse	1131	1131#	Activate
'Calling Line Identification Restriction' (pulse)				
clir	deactivate	#31	#31#	Deactivate
'Calling Line Identification Restriction'				
clir	deactivate_pulse	1231	1231#	Deactivate
'Calling Line Identification Restriction' (pulse)				
clir	test	*#31	*#31#	Check
'Calling Line Identification Restriction'				
clir	test_pulse	1331	1331#	Check
'Calling Line Identification Restriction' (pulse)				
clir	trigger	*D31	*D31#	Activate
/Deactivate 'Calling Line Identification Restriction' in trigger mode				
conference	use	*71	*71#	Use
'Conference Call, Add-on'				
ctr	activate	*96	*96#	Activate
'Call Transfer'				
ctr	activate_pulse	1196	1196#	Activate
'Call Transfer' (pulse)				
ctr	deactivate	#96	#96#	Deactivate
'Call Transfer'				
ctr	deactivate_pulse	1296	1296#	Deactivate
'Call Transfer' (pulse)				
ctr	test	*#96	*#96#	Check 'Call
Transfer'				
ctr	test_pulse	1396	1396#	Check 'Call
Transfer' (pulse)				
ctr	trigger	*D96	*D96#	Activate
/Deactivate 'Call Transfer' in trigger mode				
cw	activate	*43	*43#	Activate
'Call Waiting'				
cw	activate_pulse	1143	1143#	Activate
'Call Waiting' (pulse)				
cw	deactivate	#43	#43#	Deactivate
'Call Waiting'				
cw	deactivate_pulse	1243	1243#	Deactivate
'Call Waiting' (pulse)				
cw	test	*#43	*#43#	Check 'Call
Waiting'				

cw	test_pulse	1343	1343#	Check 'Call
Waiting' (pulse)				
cw	trigger	*D43	*D43#	Activate
/Deactivate 'Call Waiting' in trigger mode				
direct_call	activate	*53	*53*NUMBER#	Activate
'Direct call'				
direct_call	deactivate	#53	#53#	Deactivate
'Direct call'				
direct_call	test	*#53	*#53*NUMBER#	Check
'Direct call'				
direct_call	trigger	*D53	*D53*NUMBER#	Activate
/Deactivate 'Direct call' in trigger mode				
dnd	activate	*26	*26#	Activate 'Do
not Disturb'				
dnd	activate_pulse	1126	1126#	Activate 'Do
not Disturb' (pulse)				
dnd	deactivate	#26	#26#	Deactivate
'Do not Disturb'				
dnd	deactivate_pulse	1226	1226#	Deactivate
'Do not Disturb' (pulse)				
dnd	test	*#26	*#26#	Check 'Do
not Disturb'				
dnd	test_pulse	1326	1326#	Check 'Do
not Disturb' (pulse)				
dnd	trigger	*D26	*D26#	Activate
/Deactivate 'Do not Disturb' in trigger mode				
fax_to_email	use	*73	*73#	Fax to email
service				
follow_me	activate	*23	*23#	Activate
'Follow me'				
follow_me	deactivate	#23	#23#	Deactivate
'Follow me'				
follow_me	test	*#23	*#23#	Check
'Follow me'				
follow_me_no_response	activate	*25	*25#	Activate
'Follow me No Response'				
follow_me_no_response	deactivate	#25	#25#	Deactivate
'Follow me No Response'				
follow_me_no_response	set_timeout	*125	*125*BEEP_COUNT#	Set No
Response timeout for 'Follow me No Response'				
follow_me_no_response	test	*#25	*#25#	Check
'Follow me No Response'				
follow_me_no_response	test_timeout	*#125	*#125#	Check No
Response timeout for 'Follow me No Response'				
intervention	use	*09	*09*NUMBER#	Use
'Intervention'				
mcid	use	*36	*36#	Use
'Malicious Call Identification'				
meet_me_conference	create_room	*270	*270*MEET_ME_ROOM#	Create the
meet me conference room				
meet_me_conference	enter_room	*271	*271*MEET_ME_ROOM#	Enter the
meet me conference room				
message	allocate	*75	*75*NUMBER#	Use message
service				
message	free	#75	#75*NUMBER#	Use message
service				
message	manage	*#75	*#75*NUMBER#	Use message
service				
my_number	use	*123	*123#	Use 'Get
number of my phone'				
park	use_park	*57	*57#	Put a call
on park				
park	use_unpark	*58	*58#	Pick up the
parked call				
pickup	use_any	*08	*08#	Use 'Pickup'
any number in group(s)				
pickup	use_direct	*07	*07*NUMBER#	Use 'Pickup'
direct number or group				
rbp	activate	*34	*34*PIN*CODE#	Activate
'Restricting call-processes by NI and PIN'				
rbp	deactivate	#34	#34*PIN#	Deactivate

'Restricting call-processes by NI and PIN'	rbp	test	*#34	*#34*PIN#	Check
'Restricting call-processes by NI and PIN'	rbp	use	*32	*32*PIN*NUMBER#	Use
'Restricting call-processes by NI and PIN'	redial	activate	*77	*77#	Activate
'Last number redial'	redial	deactivate	#77	#77#	Deactivate
'Last number redial'	redial	test	*#77	*#77#	Check 'Last
number redial'	redial	trigger	*D77	*D77#	Activate
/Deactivate 'Last number redial' in trigger mode	redial	use	*	*#	Use 'Last
number redial'	remote_phone	activate	*70	*70*PIN*LOCAL_NUMBER#	Activate
'Remote phone'	remote_phone	deactivate	#70	#70*PIN#	Deactivate
'Remote phone'	rfc	activate	*64	*64#	Activate
'Rejection of Forwarded Calls'	rfc	activate_pulse	1164	1164#	Activate
'Rejection of Forwarded Calls' (pulse)	rfc	deactivate	#64	#64#	Deactivate
'Rejection of Forwarded Calls'	rfc	deactivate_pulse	1264	1264#	Deactivate
'Rejection of Forwarded Calls' (pulse)	rfc	test	*#64	*#64#	Check
'Rejection of Forwarded Calls'	rfc	test_pulse	1364	1364#	Check
'Rejection of Forwarded Calls' (pulse)	rfc	trigger	*D64	*D64#	Activate
/Deactivate 'Rejection of Forwarded Calls' in trigger mode	sca	activate	*60	*60*PIN#	Activate
'Selective Call Acceptance'	sca	deactivate	#60	#60*PIN#	Deactivate
'Selective Call Acceptance'	sco_black	activate	*63	*63*PIN#	Activate
'Selective Call Originating, Black list'	sco_black	deactivate	#63	#63*PIN#	Deactivate
'Selective Call Originating, Black list'	sco_white	activate	*62	*62*PIN#	Activate
'Selective Call Originating, White list'	sco_white	deactivate	#62	#62*PIN#	Deactivate
'Selective Call Originating, White list'	scr	activate	*61	*61*PIN#	Activate
'Selective Call Rejection'	scr	deactivate	#61	#61*PIN#	Deactivate
'Selective Call Rejection'	speed_dial	activate	*51	*51*CODE*NUMBER#	Activate
'Speed dial (Abbreviated dialing)'	speed_dial	deactivate	#51	#51*CODE#	Deactivate
'Speed dial (Abbreviated dialing)'	speed_dial	test	*#51	*#51*CODE#	Check 'Speed
dial (Abbreviated dialing)'	speed_dial	use	**	***CODE#	Use 'Speed
dial (Abbreviated dialing)'	teleconference	activate_subscriber_voice	*476	*476*ROOM*SUBSCRIBER#	Activate
subscriber voice of the teleconference room	teleconference	call_group	*478	*478*ROOM*GROUP#	Call group
of subscribers to the teleconference room	teleconference	call_subscriber	*473	*473*ROOM*SUBSCRIBER#	Call
subscriber to the teleconference room	teleconference	cancel_group	*479	*479*ROOM*GROUP#	Cancel group
of subscribers from the teleconference room	teleconference	cancel_subscriber	*474	*474*ROOM*SUBSCRIBER#	Cancel
subscriber from the teleconference room	teleconference	change_subscriber_voice	*475	*475*ROOM*SUBSCRIBER#	Change
subscriber voice(trigger mode) of the teleconference room	teleconference	create_room	*470	*470*ROOM#	Create the
teleconference room					

teleconference	deactivate_subscriber_voice*477		*477*ROOM*SUBSCRIBER#	Deactivate
subscriber voice of the teleconference room				
teleconference	destroy_room	*471	*471*ROOM#	Destroy the
teleconference room				
teleconference	enter_room	*472	*472*ROOM#	Enter the
teleconference room				
teleconference_manager	member	*171	*171*MEETING_ID#	Join to the
teleconference meeting by member				
vip_call	use	*99	*99#	Use VIP-call
service				
voice_page	use	*80	*80#	Use
'VoicePage' service				
voice_page_control	activate	*82	*82#	Activate
'Voice Page Control' service				
voice_page_control	deactivate	#82	#82#	Deactivate
'Voice Page Control' service				
voice_page_control	test	*#82	*#82#	Check 'Voice
Page Control' service				
voicemail	use_reader	*90	*90#	Check and
play voice mail				
voicemail	use_reader_other_number	*91	*91#	Check and
play voice mail from any number				
walkie_talkie	use	*83	*83*NUMBER#	Use 'Walkie
Talkie' service				
zone_page	use	*81	*81#	Use
'ZonePage' service in Conference mode				

#### Legend:

- W - warning column. Available values:
- D - current feature code are duplicated;

[exec at: 29.05.2019 10:20:27, exec time: 51ms, nodes: dsl@ecss1]

## set

```

.
:
/domain/<DOMAIN>/ss/feature-codes/set
:
set <Family> <FeatureKey> <FeatureCode>
:
<FAMILY> - . . ;
<FeatureKey> - , , :
    • deactivate - . ;
    • activate - . .
<FeatureCode> - , , , : 0-9, A-D, *, #.
```



"", "##21".

```

:
*97* feature- vip-call.
```

```
admin@mycelium1@ecss1#ECSS-T 000009]:/$ domain/biysk.local/ss/feature-codes/set vip_call use 97
Feature code successfully changed
```

[exec at: 29.05.2019 10:24:08, exec time: 494ms, nodes: dsl@ecss1]