

<Tab>
, - . <?>.
., ,
:

```
esr> enable 15
```

```
esr# configure
```

```
esr(config)#  
esr(config)# exit  
esr#
```

, 1.

1 – CLI

Ctrl+D	– (exit), – CLI (logout)
Ctrl+Z	(top)
Ctrl+A	
Ctrl+E	
Ctrl+U	
Ctrl+	
Ctrl+,	
Ctrl+W	
Ctrl+B	
Ctrl+F	
Ctrl+L	

```
esr# show running-config
syslog max-files 3
syslog file-size 512
syslog file esr info
syslog console info
interface gigabitethernet 1/0/1
    ip address 10.100.14.1/24
exit
interface gigabitethernet 1/0/1.101
exit
interface gigabitethernet 1/0/2
    ip address 192.168.1.1/24
    ip address 10.100.100.2/24
exit
interface gigabitethernet 1/0/2.150
    ip address 10.150.150.2/24
exit
interface gigabitethernet 1/0/2.151
    ip address 10.151.151.15/24
exit
interface gigabitethernet 1/0/3
    ip address dhcp enable
exit
interface gigabitethernet 1/0/5.55
More? Enter - next line; Space - next page; Q - quit; R - show the rest.
```

```
:  
esr# terminal datadump
```



admin password

1,10 15 :

- 1 – ;
- 10 – , , , ;
- 15 – .

15 :

```
(esr)> enable  
(esr)#
```

:

```
(esr)# disable  
(esr)>
```

«|» :

- begin – , ;
- count – , (,);
- counter – ;
- include – , ;
- exclude – , ;
- until – , .

:

```
- . , «[]». . . «^», . , . :
```

- [-az] - 'a', 'z' '-';
- [a-z] - 'a' 'z' .

```
- :
```

- ^ - ;
- \$ - ;
- . - ;
- * - .

```
«show running-config syslog» :
```

```
esr# show running-config syslog
syslog max-files 3
syslog file-size 512
syslog file default info
```

```
«show running-config syslog» c «begin»:
```

```
esr# show running-config syslog | begin file-size
syslog file-size 512
syslog file default info
```

```
«show running-config syslog» c «include»:
```

```
esr# show running-config syslog | include file-size
syslog file-size 512
```

```
«show running-config syslog» c «exclude»:
```

```
esr# show running-config syslog | exclude file-size
syslog max-files 3
syslog file default info
```

```
:
```

```
esr# show interfaces status | include "^\w+te.*"
te1/0/1      Up      Down    1500      a8:f9:4b:aa:05:d9
te1/0/2      Up      Down    1500      a8:f9:4b:aa:05:da
esr# show interfaces status | include "^\w+gi1/0/1[2568]"
gi1/0/12     Up      Down    1500      a8:f9:4b:aa:05:cc
gi1/0/15     Up      Down    1500      a8:f9:4b:aa:05:cf
gi1/0/16     Up      Down    1500      a8:f9:4b:aa:05:d0
gi1/0/18     Up      Down    1500      a8:f9:4b:aa:05:d2
esr# show interfaces status | include "^\w+tg1 -"
bridge 1     Up      Up      1500      a8:f9:4b:aa:05:c0
bridge 2     Up      Up      1500      a8:f9:4b:aa:05:c0
```

```
, show, . , . :
```

- > - ;
- >> - ;

- flash:data/<FILE> - flash:data;
- usb://<USB-NAME>/<FILE> - USB- <USB-NAME>;
- mmc://<MMC-NAME>/<FILE> - USB- <MMC-NAME>.