

[LTP-] VLAN isolation

- . vlan, pon-port 0, front-port 1 front-port 6, VLAN 30.
- 2 pon-port, 3 uplink , .



0 1 , , , 2 .

```
LTP-8X# switch
LTP-8X(switch)# configure
LTP-8X(switch)(config)# isolation group 2
LTP-8X(switch)(config-is-group)# allow pon-port 0
LTP-8X(switch)(config-is-group)# exit
LTP-8X(switch)(config)# isolation group 3
LTP-8X(switch)(config-is-group)# allow front-port 1
LTP-8X(switch)(config-is-group)# allow front-port 6
LTP-8X(switch)(config-is-group)# exit
LTP-8X(switch)(config)# commit
```

VLAN 30:

```
LTP-8X(switch)(config)# vlan 30
LTP-8X(switch)(config-vlan)# isolation enable
```

:

```
LTP-8X(switch)(config-vlan)# isolation assign group 2 to front-port 1
LTP-8X(switch)(config-vlan)# isolation assign group 2 to front-port 6
LTP-8X(switch)(config-vlan)# isolation assign group 3 to pon-port 0
LTP-8X(switch)(config-vlan)# exit
LTP-8X(switch)(config)# commit
```

:

```
LTP-8X# switch
LTP-8X(switch)# show isolation group 2
LTP-8X(switch)# show isolation vlan 30
```

- . front-port / port-channel - 0, pon-port - 1.

```
LTP-8X(switch)(config)# vlan 30
LTP-8X(switch)(config-vlan)# isolation assign group 0 to front-port 1
LTP-8X(switch)(config-vlan)# isolation assign group 0 to front-port 6
LTP-8X(switch)(config-vlan)# isolation assign group 1 to pon-port 0
LTP-8X(switch)(config-vlan)# exit
LTP-8X(switch)(config)# commit
```