

PLC8 board ONT configuration profile management.

SCRIPTING profile

- [scripting](#)
- [name](#)
- [description](#)
- [show profile scripting](#)

In the **profile scripting** mode, the ONT script configuration profiles are configured.

After configuration, the **cross-connect** profile can be assigned to a specific template or directly in the ONT configuration.

The full description of the functionality can be clarified by contacting the technical support service.

scripting

This command allows to create a new profile and/or switch to its configuration mode.

The use of a negative form (no) of the command removes the profile.

Syntax

```
profile scripting <NAME>
[no] profile scripting <NAME>
```

Parameters

<NAME> – profile name, case sensitive.

Command mode

CONFIG

Example

```
ma4000(config)# profile scripting name
ma4000(config-scripting)("name")#
```

name

The command changes the name of the configured profile.

Syntax

```
name <STRING>
```

Parameters

<STRING> – profile name, case sensitive.

Command mode

PROFILE SCRIPTING

Example

```
ma4000(config-scripting)("name")# name test
```

description

This command allows to add a description for the profile to be configured.

The use of a negative form (no) of the command removes description.

Syntax

```
description <STRING>  
[no] description <STRING>
```

Parameters

<STRING> – text description.

Command mode

PROFILE SCRIPTING

Example

```
ma4000(config-scripting)("name")# description doc
```

show profile scripting

This command allows to view the existing profiles, view the configuration of the specified profile.

Syntax

```
show profile scripting <NAME>
```

Parameters

<NAME> – profile name, optional parameter, case sensitive.

If no profile name is specified – the list of all profiles of this type is displayed, if the name is specified – the configuration of this profile is displayed.

Command mode

ROOT

Example 1

```
ma4000# show profile scripting  
##           Name      Description  
1      scripting-00  ONT Profile Scripting 0
```

Example 2

```
ma4000# show profile scripting scripting-00  
Name:           'scripting-00'  
Description:    'ONT Profile Scripting 0'
```