

TAU16/TAU24/TAU32m/TAU36/TAU72.

, web- (telnet, RS-232), RS-232. , :

- (: TERATERM);
- TFTP .

- a. Ethernet .
- b. COM .
- c. .
- d. 115200, 8, , 1, .
- e. TFTP- chagall (, TFTP). 300 firmware.elf, initrd.300, zImage.300 reserv_soft.zip .
- f. . stop :

```
U-Boot 1.1.6 (Nov 13 2008 - 16:24:39) Mindspeed 0.06.2-candidate1
DRAM: 128 MB
Concerto Flash Subsystem Initialization
found am29gl512 flash at B8000000
Flash: 64 MB
NAND: 64 MiB
In: serial
Out: serial
Err: serial
Reserve MSP memory
Net: concerto\_gemac0: config phy 0, speed 1000, duplex full
      concerto\_gemac1: config phy 1, speed 1000, duplex full
      concerto\_gemac0, concerto\_gemac1
      Write 'stop' to stop autoboot (3 sec)..
FXS-72>>
```

- g. IP- :
set ipaddr <ipaddr>

<ipaddr> - IP- TAU.
: set ipaddr 192.168.16.112
- h. :
set netmask <netmask>

<netmask> - .
: set netmask 255.255.255.0
- i. IP- TFTP-:
set serverip <tftp-ip>

<tftp-ip> - IP- , TFTP-.
: set serverip 192.168.16.44
- j. mii /
- k. linux run updatecsp
- l. - run updatemsp
- m. run updatefs
- n. run bootcmd