

v1.16_ (radius)

RADIUS. eltex-ngw radacct-stop (Acct-Status-Type = Stop), Calling-Station-Id .

:

1. /etc/eltex-ngw/rtk_sbc.conf NUMBERS_FOR_INCOMING_CALLS , . RADIUS_PORT RADIUS_SECRET radius-secret. PHONE_NUMBER_PREFIX - SBC. :

```
RADIUS_PORT=8041
RADIUS_SECRET=1234

# prefix to be applied to the phone number in Calling-Station-Id attribute
PHONE_NUMBER_PREFIX=

# numbers for receiving incoming calls
# comma is a separator
NUMBERS_FOR_INCOMING_CALLS=88001230123
```

2. /etc/eltex-ngw/notification.properties :

```
sms.gate.incoming.call.config=rtk_sbc.conf
```

3. eltex-ngw.

:

acct-stop radclient:

```
echo 'Acct-Status-Type = Stop, Calling-Station-Id = "<sip:+79234567890@exmple.ru>"' | radclient localhost:8041
acct eltexsecret
```

, eltex-ngw rtk_sbc <sip: @__> (<sip:79234567890@a>). , , :

```
2017-10-10 00:00:00.001 [SbcRadiusReceiver] WARN SbcRadiusReceiver:151 - Could not extract phone from Calling-Station-Id "79234567890"
```

radacct, eltex-ngw:

> Frame 1: 99 bytes on wire (792 bits), 99 bytes captured (792 bits)

> Ethernet II, Src: PcsCompu_6d:37:2b (08:00:27:6d:37:2b), Dst: PcsCompu_a7:99:e6 (08:00:27:a7:99:e6)

> Internet Protocol Version 4, Src: 192.168.15.213, Dst: 192.168.15.212

> User Datagram Protocol, Src Port: 33476, Dst Port: 8041

▼ RADIUS Protocol

Code: Accounting-Request (4)

Packet identifier: 0x92 (146)

Length: 57

Authenticator: 6d69f6e9ef8617b2ee5f14234fe896a7

▼ Attribute Value Pairs

▼ AVP: l=6 t=Acct-Status-Type(40): Stop(2)

AVP Type: 40

AVP Length: 6

Acct-Status-Type: Stop (2)

▼ AVP: l=31 t=Calling-Station-Id(31): <sip:+79234567890@example.ru>

AVP Type: 31

AVP Length: 31

Calling-Station-Id: <sip:+79234567890@example.ru>

:



acct-stop.pcap